

Cable Wire Device Connections

Blue/GP-Panel

Cable Wires	Circuit ID Circuit Name	Device Name Terminal Wire Count	Device Type Device Terminal Connection
1G-03/05 To/From: "Blue/XL-Dim" 14-3			
White "Neutral"	1G-03 (Lounge Bar: LV LED Counter Lighting)	"Dimmer (Lower Stair: Ceiling & Lounge Bar: Counter)" 1	Dimmer, Type 1, Dual 4A Control In / B: AC2
	1G-05 (Photo Booth: Overhead Lighting)	"Dimmer (Photo Booth: Front & Overhaed)" 1	Dimmer, Type 2, Dual 5A #2 Control In / B: AC1
Black "Switched"	1G-03 (Lounge Bar: LV LED Counter Lighting)	"Dimmer (Lower Stair: Ceiling & Lounge Bar: Counter)" 1	Dimmer, Type 1, Dual 4A Control In / B: AC1
Red "Switched"	1G-05 (Photo Booth: Overhead Lighting)	"Dimmer (Photo Booth: Front & Overhaed)" 1	Dimmer, Type 2, Dual 5A #2 Control In / B: AC2
1G-04 To/From: "Blue/XL-Dim" 14-2			
White "Neutral"	1G-04 (Photo Booth: Front Lighting)	"Dimmer (Photo Booth: Front & Overhaed)" 1	Dimmer, Type 2, Dual 5A #2 Control In / A: AC2
Black "Switched"	1G-04 (Photo Booth: Front Lighting)	"Dimmer (Photo Booth: Front & Overhaed)" 1	Dimmer, Type 2, Dual 5A #2 Control In / A: AC1
1G-20 To/From: Lounge Bar 12-3			
White "Neutral"	1G-20 Lounge Bar: Outlet for Instant Hot	"Lounge Bar Instant Hot SSR" 1	Relay, Solid State (25A) #4 Power Output / Neutral
Black "Hot"	1G-20 Lounge Bar: Outlet for Instant Hot	"Lounge Bar Instant Hot SSR" 1	Relay, Solid State (25A) #4 Power Output / Hot
Red "Switched"	1G-20 Lounge Bar: Outlet for Instant Hot	"Lounge Bar Instant Hot SSR" 1	Relay, Solid State (25A) #4 Power Output / 2 (Output)
1G-21 To/From: "Blue/XL-HVRB" 14-2			
White "Neutral"	1G-21 (Shop: Work Area Lights B (Aux))	"Emerg Lighting: Shop: Work Area Lights 24 Vdc DPDT" 1	Relay, DPDT, 24 Vdc (Plug-In) Input / NC 2 (T3)
Black "Switched"	1G-21 (Shop: Work Area Lights B (Aux))	"Emerg Lighting: Shop: Work Area Lights 24 Vdc DPDT" 1	Relay, DPDT, 24 Vdc (Plug-In) Input / NC 1 (T1)
1G-22 To/From: "Yellow/CB-Panel/Emer" 14-2			
White "Neutral"	1G-22 (Emergency Lighting)	"Emerg Lighting: Shop: Work Area Lights 24 Vdc DPDT" 1	Relay, DPDT, 24 Vdc (Plug-In) Input / NO 2 (T6)
Black "Hot"	1G-22 (Emergency Lighting)	"Emerg Lighting: Shop: Work Area Lights 24 Vdc DPDT" 1	Relay, DPDT, 24 Vdc (Plug-In) Input / NO 1 (T4)
1G-30 To/From: "Blue/CB-Panel" 12-2			
White "Neutral"	1G-30 (Lounge Bar: Outlet for Instant Hot)	"Lounge Bar Instant Hot SSR" 1	Relay, Solid State (25A) #4 NO Input / Neutral
Black "Hot"	1G-30 (Lounge Bar: Outlet for Instant Hot)	"Lounge Bar Instant Hot SSR" 1	Relay, Solid State (25A) #4 NO Input / 1 (Output)
1G-32 To/From: "Yellow/CB-Panel/OffP" 14-2			
White "Neutral"	1G-32 (Bedroom 2/3: Towel Warmer)	"Bedroom 2/3 Bath Heater SSR" 1	Relay, Solid State (25A) #5 NO Input / Neutral

Cable Wire Device Connections

Blue/GP-Panel

Cable Wires	Circuit ID Circuit Name	Device Name Terminal Wire Count	Device Type Device Terminal Connection
Black "Hot"	1G-32 (Bedroom 2/3: Towel Warmer)	"Bedroom 2/3 Bath Heater SSR" 1	Relay, Solid State (25A) #5 NO Input / 1 (Output)
1G-33 To/From: "Blue/CB-Panel" & Others 14-2			
White "Neutral"	1G-33 Blue/CN-Panel Outlet	"Line Power Duplex Outlet" 1	Outlet, Duplex (15A) Power In (120 Vac) / Neutral
Black "Hot"	1G-33 Blue/CN-Panel Outlet	"Line Power Duplex Outlet" 1	Outlet, Duplex (15A) Power In (120 Vac) / Hot
1G-36 To/From: "Yellow/CB-Panel/OffP" 12-2			
White "Neutral"	1G-36 (Changing Room A: Heater)	"Changing Room A Heater SSR" 1	Relay, Solid State (25A) #1 NO Input / Neutral
Black "Hot"	1G-36 (Changing Room A: Heater)	"Changing Room A Heater SSR" 1	Relay, Solid State (25A) #1 NO Input / 1 (Output)
1G-37 To/From: "Yellow/CB-Panel/OffP" 12-2			
White "Neutral"	1G-37 (Changing Room B: Heater)	"Changing Room B Heater SSR" 1	Relay, Solid State (25A) #2 NO Input / Neutral
Black "Hot"	1G-37 (Changing Room B: Heater)	"Changing Room B Heater SSR" 1	Relay, Solid State (25A) #2 NO Input / 1 (Output)
1G-38 To/From: "Yellow/CB-Panel/OffP" 14-2			
White "Neutral"	1G-38 (Bedroom 2/3 Bath: Heater)	"Bedroom 2/3 Bath Heater SSR" 1	Relay, Solid State (25A) #3 NO Input / Neutral
Black "Hot"	1G-38 (Bedroom 2/3 Bath: Heater)	"Bedroom 2/3 Bath Heater SSR" 1	Relay, Solid State (25A) #3 NO Input / 1 (Output)
1G-59 To/From: "Blue/CB-Panel" 14-2			
White "Hot (Pole 2)"	1G-59 Blue: Dimmed LV LED Lights	LED Lighting 24 Vdc Power 1	Power Supply, 24 Vdc, 480W DIN Power In (120/240 Vac) / N
Black "Hot (Pole 1)"	1G-59 Blue: Dimmed LV LED Lights	LED Lighting 24 Vdc Power 1	Power Supply, 24 Vdc, 480W DIN Power In (120/240 Vac) / L

Cable Wire Device Connections

Blue/GP-Panel

Cable Wires	Circuit ID Circuit Name	Device Name Terminal Wire Count	Device Type Device Terminal Connection
1G-60	To/From: No External Connections		18-2
Black "24 Vdc Return"	1G-60 LED Lighting 24 Vdc Power	LED Lighting 24 Vdc Power 1	Power Supply, 24 Vdc, 480W DIN Power Output / -
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (Lower Stair: Ceiling & Lounge Bar: Counter)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / A: Com-
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (Lower Stair: Ceiling & Lounge Bar: Counter)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / B: Com-
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (Photo Booth: Front & Overhaed)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / A: Com-
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (Photo Booth: Front & Overhaed)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / B: Com-
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (-spare- & BR 2/3 Bath: Toe Kick)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / A: Com-
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (-spare- & BR 2/3 Bath: Toe Kick)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / B: Com-
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (Driveway: Railing & Walkout Patio: Railing)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / A: Com-
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (Driveway: Railing & Walkout Patio: Railing)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / B: Com-
Red "+24 Vdc"	1G-60 LED Lighting 24 Vdc Power	LED Lighting 24 Vdc Power 1	Power Supply, 24 Vdc, 480W DIN Power Output / +
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (Lower Stair: Ceiling & Lounge Bar: Counter)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / A: Pwr+
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (Lower Stair: Ceiling & Lounge Bar: Counter)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / B: Pwr+
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (Photo Booth: Front & Overhaed)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / A: Pwr+
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (Photo Booth: Front & Overhaed)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / B: Pwr+
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (-spare- & BR 2/3 Bath: Toe Kick)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / A: Pwr+
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (-spare- & BR 2/3 Bath: Toe Kick)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / B: Pwr+
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (Driveway: Railing & Walkout Patio: Railing)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / A: Pwr+
	1G-60 LED Lighting 24 Vdc Power	"Dimmer (Driveway: Railing & Walkout Patio: Railing)" 1	Dimmer, Type 1, Dual 4A Power In (12 / 24 Vdc) / B: Pwr+
1G-A07	To/From: "White/CN-Panel/2"		22-8
Red "+24 Vdc"	1G-A07 Changing Room A Heater Drive	"Changing Room A Heater SSR" 1	Relay, Solid State (25A) #1 Control In / 3 (Input +)
	1G-A08 Changing Room B Heater Drive	"Changing Room B Heater SSR" 1	Relay, Solid State (25A) #2 Control In / 3 (Input +)
	1G-A09 Bedroom 2/3 Bath Heater Drive	"Bedroom 2/3 Bath Heater SSR" 1	Relay, Solid State (25A) #3 Control In / 3 (Input +)
	1G-A10 Lounge: Instant Hot Drive	"Lounge Bar Instant Hot SSR" 1	Relay, Solid State (25A) #4 Control In / 3 (Input +)
	1G-A11 Bedroom 2/3 Bath: Towel Warmer Drive	"Bedroom 2/3 Bath Heater SSR" 1	Relay, Solid State (25A) #5 Control In / 3 (Input +)
White "Switched"	1G-A07 Changing Room A Heater Drive	"Changing Room A Heater SSR" 1	Relay, Solid State (25A) #1 Control In / 4 (Input -)

Cable Wire Device Connections

Blue/GP-Panel

Cable Wires	Circuit ID Circuit Name	Device Name Terminal Wire Count	Device Type Device Terminal Connection
Green "Switched"	1G-A08 Changing Room B Heater Drive	"Changing Room B Heater SSR" 1	Relay, Solid State (25A) #2 Control In / 4 (Input -)
Brown "Switched"	1G-A09 Bedroom 2/3 Bath Heater Drive	"Bedroom 2/3 Bath Heater SSR" 1	Relay, Solid State (25A) #3 Control In / 4 (Input -)
Blue "Switched"	1G-A10 Lounge: Instant Hot Drive	"Lounge Bar Instant Hot SSR" 1	Relay, Solid State (25A) #4 Control In / 4 (Input -)
Orange "Switched"	1G-A11 Bedroom 2/3 Bath: Towel Warmer Drive	"Bedroom 2/3 Bath Heater SSR" 1	Relay, Solid State (25A) #5 Control In / 4 (Input -)
1G-A33 To/From: "White/CN-Panel/2" 22-4 (S)			
Black "Return"	1G-A33 Blue GP: Cabinet Fan Drive	"Enclosure Vent Fan & Temp Sensor" 1	Fan & Sensor Kit, Cabinet Fan Power In / Fan -
Red "Signal"	1G-A33 Blue GP: Cabinet Fan Drive	"Enclosure Vent Fan & Temp Sensor" 1	Fan & Sensor Kit, Cabinet Fan Power In / Fan +
White "Select"	1G-S21 Blue GP: Cabinet Temperature	"Enclosure Vent Fan & Temp Sensor" 1	Fan & Sensor Kit, Cabinet Temp Sensor Output / (Sensor) +
Green "Signal"	1G-S21 Blue GP: Cabinet Temperature	"Enclosure Vent Fan & Temp Sensor" 1	Fan & Sensor Kit, Cabinet Temp Sensor Output / (Sensor) -
Shield "Shield"	1G-S21 Blue GP: Cabinet Temperature	"Enclosure Vent Fan & Temp Sensor" 1	Fan & Sensor Kit, Cabinet Temp Sensor Output / GND
1G-A45 To/From: "White/CN-Panel/2" 22-4			
Red "+24 Vdc"	1G-A45 Shop Lighting Transfer Drive	"Ermerg Lighting: Shop: Work Area Lights 24 Vdc DPDT" 1	Relay, DPDT, 24 Vdc (Plug-In) Control In / Coil +(TA)
White "Switched"	1G-A45 Shop Lighting Transfer Drive	"Ermerg Lighting: Shop: Work Area Lights 24 Vdc DPDT" 1	Relay, DPDT, 24 Vdc (Plug-In) Control In / Coil -(TB)
1G-T03 To/From: Lounge Bar 12-2			
White "Power Return"	1G-T03 Lounge: LV LED Counter Lighting	"Dimmer (Lower Stair: Ceiling & Lounge Bar: Counter)" 1	Dimmer, Type 2, Dual 5A #1 Power Output / B: Com-
Black "+24 Vdc"	1G-T03 Lounge: LV LED Counter Lighting	"Dimmer (Lower Stair: Ceiling & Lounge Bar: Counter)" 1	Dimmer, Type 2, Dual 5A #1 Power Output / B: Load+
1G-T04a To/From: Photo Booth 12-2			
White "Power Return"	1G-T04a Photo Booth: LED Overhead Puck Lighting (a)	"Dimmer (Photo Booth: Front & Overhaed)" 2	Dimmer, Type 2, Dual 5A #2 Power Output / A: Com-
Black "+24 Vdc"	1G-T04a Photo Booth: LED Overhead Puck Lighting (a)	"Dimmer (Photo Booth: Front & Overhaed)" 2	Dimmer, Type 2, Dual 5A #2 Power Output / A: Load+
1G-T04b To/From: Photo Booth 14-2			
White "Neutral"	1G-T04b Photo Booth: LED Overhead Puck Lighting (b)	"Dimmer (Photo Booth: Front & Overhaed)" 2	Dimmer, Type 2, Dual 5A #2 Power Output / A: Com-
Black "Switched"	1G-T04b Photo Booth: LED Overhead Puck Lighting (b)	"Dimmer (Photo Booth: Front & Overhaed)" 2	Dimmer, Type 2, Dual 5A #2 Power Output / A: Load+

Cable Wire Device Connections

Blue/GP-Panel

Cable Wires	Circuit ID Circuit Name	Device Name Terminal Wire Count	Device Type Device Terminal Connection
1G-T05 To/From: Lounge Bar 12-2			
White "Power Return"	1G-T05 Photo Booth: LV LED Front Lighting	"Dimmer (Photo Booth: Front & Overhaed)" 1	Dimmer, Type 2, Dual 5A #2 Power Output / B: Com-
Black "+24 Vdc"	1G-T05 Photo Booth: LV LED Front Lighting	"Dimmer (Photo Booth: Front & Overhaed)" 1	Dimmer, Type 2, Dual 5A #2 Power Output / B: Load+
1H-08 To/From: Changing Room A 12-2			
White "Neutral"	1H-08 Changing Room A: Heater	"Changing Room A Heater SSR" 1	Relay, Solid State (25A) #1 Power Output / Neutral
Black "Switched"	1H-08 Changing Room A: Heater	"Changing Room A Heater SSR" 1	Relay, Solid State (25A) #1 Power Output / 2 (Output)
1H-09 To/From: Changing Room B 12-2			
White "Neutral"	1H-09 Changing Room B: Heater	"Changing Room B Heater SSR" 1	Relay, Solid State (25A) #2 Power Output / Neutral
Black "Switched"	1H-09 Changing Room B: Heater	"Changing Room B Heater SSR" 1	Relay, Solid State (25A) #2 Power Output / 2 (Output)
1K-04 To/From: Shop 14-2			
White "Neutral"	1K-04 Shop: Work Area Lights B (Aux)	"Ermerg Lighting: Shop: Work Area Lights 24 Vdc DPDT" 1	Relay, DPDT, 24 Vdc (Plug-In) Output / Com 2 (T9)
Black "Switched"	1K-04 Shop: Work Area Lights B (Aux)	"Ermerg Lighting: Shop: Work Area Lights 24 Vdc DPDT" 1	Relay, DPDT, 24 Vdc (Plug-In) Output / Com 1 (T7)
1M-01 To/From: "White/XL-Dim" 14-2			
White "Neutral"	1M-01 Lower Stairway: Ceiling Lights	"Dimmer (Lower Stair: Ceiling & Lounge Bar: Counter)" 1	Dimmer, Type 1, Dual 4A Control In / A: AC1
Black "Switched"	1M-01 Lower Stairway: Ceiling Lights	"Dimmer (Lower Stair: Ceiling & Lounge Bar: Counter)" 1	Dimmer, Type 1, Dual 4A Control In / A: AC2
1M-T01 To/From: Lower Stairway 14-2			
White "Neutral"	1M-T01 Lower Stairway: LV LED Ceiling Lighting	"Dimmer (Lower Stair: Ceiling & Lounge Bar: Counter)" 1	Dimmer, Type 2, Dual 5A #1 Power Output / A: Com-
Black "Switched"	1M-T01 Lower Stairway: LV LED Ceiling Lighting	"Dimmer (Lower Stair: Ceiling & Lounge Bar: Counter)" 1	Dimmer, Type 2, Dual 5A #1 Power Output / A: Load+
2G-06 To/From: "White/XL-Dim" 14-2			
White "Neutral"	2G-06 Lower Stairway: LV LED Tread Lighting	"Dimmer 10A (Lower Stairway: LV LED Tread)" 1	Dimmer, Single 10A Control In / : AC2
Black "Switched"	2G-06 Lower Stairway: LV LED Tread Lighting	"Dimmer 10A (Lower Stairway: LV LED Tread)" 1	Dimmer, Single 10A Control In / : AC1
2G-09 To/From: BR 2/3 Bath 14-2			
White "Neutral"	2G-09 BR 2/3 Bath: Heater	"Bedroom 2/3 Bath Heater SSR" 1	Relay, Solid State (25A) #3 Power Output / Neutral

Cable Wire Device Connections

Blue/GP-Panel

Cable Wires	Circuit ID Circuit Name	Device Name Terminal Wire Count	Device Type Device Terminal Connection
Black "Switched"	2G-09 BR 2/3 Bath: Heater	"Bedroom 2/3 Bath Heater SSR" 1	Relay, Solid State (25A) #3 Power Output / 2 (Output)
2G-11		To/From: BR 2/3 Bath	14-2
White "Neutral"	2G-11 BR 2/3 Bath: Towel Warmer	"Bedroom 2/3 Bath Heater SSR" 1	Relay, Solid State (25A) #5 Power Output / Neutral
Black "Switched"	2G-11 BR 2/3 Bath: Towel Warmer	"Bedroom 2/3 Bath Heater SSR" 1	Relay, Solid State (25A) #5 Power Output / 2 (Output)
2G-17		To/From: "Blue/XL-Dim"	14-2
White "Neutral"	2G-17 BR 2/3 Bath: Toe-Kick Light	"Dimmer (-spare- & BR 2/3 Bath: Toe Kick)" 1	Dimmer, Type 1, Dual 4A Control In / B: AC1
Black "Switched"	2G-17 BR 2/3 Bath: Toe-Kick Light	"Dimmer (-spare- & BR 2/3 Bath: Toe Kick)" 1	Dimmer, Type 1, Dual 4A Control In / B: AC2
2G-T06		To/From: Lower Stairway	14-2
White "Power Return"	2G-T06 Lower Stairway: LV LED Tread Lighting	"Dimmer 10A (Lower Stairway: LV LED Tread)" 1	Dimmer, Single 10A Power Output / : Com-
Black "+24 Vdc"	2G-T06 Lower Stairway: LV LED Tread Lighting	"Dimmer 10A (Lower Stairway: LV LED Tread)" 1	Dimmer, Single 10A Power Output / : Load+
2G-T17		To/From: BR 2/3 Bath	14-2
White "Power Return"	2G-T17 BR 2/3 Bath: LV LED Toe-Kick Lighting	"Dimmer (-spare- & BR 2/3 Bath: Toe Kick)" 1	Dimmer, Type 1, Dual 4A Power Output / B: Com-
Black "+24 Vdc"	2G-T17 BR 2/3 Bath: LV LED Toe-Kick Lighting	"Dimmer (-spare- & BR 2/3 Bath: Toe Kick)" 1	Dimmer, Type 1, Dual 4A Power Output / B: Load+
2L-10		To/From: "White/XL-Dim"	14-2
White "Neutral"	2L-10 Driveway: Railing Lighting	"Dimmer (Driveway: Railing & Walkout Patio: Railing)" 1	Dimmer, Type 1, Dual 4A Control In / A: AC1
Black "Switched"	2L-10 Driveway: Railing Lighting	"Dimmer (Driveway: Railing & Walkout Patio: Railing)" 1	Dimmer, Type 1, Dual 4A Control In / A: AC2
2L-T10		To/From: "White/GP-Panel/2"	14-2
White "Neutral"	2L-T10 Driveway: Railing Lighting	"Dimmer (Driveway: Railing & Walkout Patio: Railing)" 1	Dimmer, Type 2, Dual 5A #3 Power Output / A: Com-
Black "Switched"	2L-T10 Driveway: Railing Lighting	"Dimmer (Driveway: Railing & Walkout Patio: Railing)" 1	Dimmer, Type 2, Dual 5A #3 Power Output / A: Load+
2M-11		To/From: "Blue/XL-HVRB"	14-2
White "Neutral"	2M-11 Blue Utility Area: North Landscape Lighting	"Landscape Lighting Transformer, North" 1	Transformer, 12 Vac, 100W (8A) Power In (120 Vac) / Primary B
Black "Switched"	2M-11 Blue Utility Area: North Landscape Lighting	"Landscape Lighting Transformer, North" 1	Transformer, 12 Vac, 100W (8A) Power In (120 Vac) / Primary A

Cable Wire Device Connections

Blue/GP-Panel

Cable Wires	Circuit ID Circuit Name	Device Name Terminal Wire Count	Device Type Device Terminal Connection
2M-18		To/From: "Blue/XL-Dim"	14-2
White "Neutral"	2M-18 Walkout Patio: Railing Lighting	"Dimmer (Driveway: Railing & Walkout Patio: Railing)" 1	Dimmer, Type 1, Dual 4A Control In / B: AC1
Black "Switched"	2M-18 Walkout Patio: Railing Lighting	"Dimmer (Driveway: Railing & Walkout Patio: Railing)" 1	Dimmer, Type 1, Dual 4A Control In / B: AC2
2M-T11		To/From: Walkout Patio	10-2
White "Line A"	2M-T11 Stone Stairs: Landscape Lighting	"Landscape Lighting Transformer, North" 1	Transformer, 12 Vac, 100W (8A) Power Output / Secondary A
Black "Line B"	2M-T11 Stone Stairs: Landscape Lighting	"Landscape Lighting Transformer, North" 1	Transformer, 12 Vac, 100W (8A) Power Output / Secondary B
2M-T18		To/From: Patio	14-2
White "Neutral"	2M-T18 Patio: Railing Lighting	"Dimmer (Driveway: Railing & Walkout Patio: Railing)" 1	Dimmer, Type 2, Dual 5A #3 Power Output / B: Com-
Black "Switched"	2M-T18 Patio: Railing Lighting	"Dimmer (Driveway: Railing & Walkout Patio: Railing)" 1	Dimmer, Type 2, Dual 5A #3 Power Output / B: Load+